

Accurate calculation of eigenvalues and eigenfunctions. I: Symmetric potentials

Francisco M. Fernández

INIFTA (UNLP, CCT La Plata-CONICET),

División Química Teórica, Diag. 113 y 64 (S/N),

Sucursal 4, Casilla de Correo 16, 1900 La Plata, Argentina

Abstract

We describe a method for the calculation of accurate energy eigenvalues and expectation values of observables of separable quantum–mechanical models. We discuss the application of the approach to one–dimensional anharmonic oscillators with symmetric potential–energy functions.

I. INTRODUCTION

Some time ago we developed a new method for the calculation of eigenvalues and eigenfunctions of the Schrödinger equation for separable problems. We first applied it to bound states^{1,2,3,4,5,6,7} but later we found that it also applied to resonances or metastable states^{8,9,10,11,12}, as well as to some strange complex eigenvalues¹³.

Although the method only applies to separable quantum-mechanical problems it exhibits many interesting features that may be suitable for the discussion at a graduate, or advance undergraduate level. The teaching of the approach may be greatly facilitated by available computer algebra systems (CAS) that enable one to carry out the necessary calculation without much effort or special programming ability.

In this paper we introduce the method and apply it to the one-dimensional Schrödinger equation with a symmetric potential. In order to make this article more comprehensive, in Sec. II we discuss the standard power-series treatment of the harmonic oscillator. In Sec. III we develop the method from the known solutions of the harmonic oscillator. In Sec. IV we generalize it and apply it to some anharmonic oscillators with symmetric potentials. In Sec. V we discuss the phenomenon of multiplicity of roots that is one of the particular features of the approach. In Sec. VI we address the occurrence of meaningful spurious roots which is another peculiar feature of the method. In Sec. VII we consider the eigenfunctions and the calculation of expectation values. In Sec. we apply the method to a simple double-well oscillator. In Sec. IX we draw some conclusions on the teaching and utility of the procedure.

II. THE HARMONIC OSCILLATOR

In order to facilitate the introduction of the new approach and the understanding of most of its special features we first discuss an standard approach to the harmonic oscillator. For simplicity we assume that we have rewritten the Hamiltonian operator in dimensionless form as $\hat{H} = \hat{p}^2 + V(\hat{x})$ that in the coordinate representation reads $\hat{H} = -d^2/dx^2 + V(x)$. Thus, the Schrödinger equation for the harmonic oscillator reads

$$\psi''(x) + (E - x^2)\psi(x) = 0, \quad \psi(x \rightarrow \pm\infty) = 0 \quad (1)$$

The logarithmic derivative $y(x) = \psi'(x)/\psi(x)$ satisfies the Riccati equation $y'(x) + y(x)^2 - x^2 + E = 0$. For large values of $|x|$ we find that $y(x) \sim \pm x$ and $\psi(x) \sim e^{\pm x^2/2}$. We appreciate that there are two solutions that we may call convergent $\psi_c(x)$ and divergent $\psi_d(x)$ with asymptotic behaviours $\psi_c(x) \sim e^{-x^2/2}$ and $\psi_d(x) \sim e^{x^2/2}$ at large values of $|x|$. The most general solution is a linear combination of both: $\psi(x) = C_1(E)\psi_c(x) + C_2(E)\psi_d(x)$. The allowed values of the energy E are the roots $E_0, E_1, \dots$ of $C_2(E) = 0$. Such eigenvalues E_n are consistent with a square integrable function $\int_{-\infty}^{\infty} |\psi|^2 dx < \infty$ given in this case by $\psi_c(x)$.

A textbook method for the solution of the Schrödinger equation for the harmonic oscillator is based on a power-series expansion of the solution that we write as¹⁴

$$\psi(x) = e^{-x^2/2} \sum_{j=0}^{\infty} c_j x^{2j+s} \quad (2)$$

where s determines the behaviour of $\psi(x)$ at origin. The coefficients c_j satisfy the recurrence relation $(2j + s + 1)(2j + s + 2)c_{j+1} + [E - 1 - 2(2j + s)]c_j = 0$, and $c_0 \neq 0$ provided that $s = 0$ or $s = 1$ that give rise to the even or odd states, respectively.

One can prove that for arbitrary values of E the series in equation (2) behaves asymptotically as e^{x^2} and the divergent contribution to the eigenfunction $\psi(x)$ would dominate at large $|x|$. The eigenfunction will not be square integrable unless the otherwise infinite series in equation (2) becomes a polynomial, which occurs when $E = E_n = 2n + 1$, $n = 2\nu + s = 0, 1, \dots$, $\nu = 0, 1, \dots$. When $E = E_n$ then $c_{\nu+1} = 0$ and $c_j = 0$ for all $j \geq \nu + 1$. The eigenfunctions then read

$$\begin{aligned} \psi_n(x) &= N_n x^s P_n(x) e^{-x^2/2}, \quad P_n = \sum_{j=0}^{\nu} c_{j,n} x^{2j+s} \\ c_{j+1,n} &= \frac{4(j - \nu)c_{j,n}}{(2j + s + 1)(2j + s + 2)}, \quad j = 0, 1, \dots, \nu \end{aligned} \quad (3)$$

The polynomials $x^s P_n(x)$ are proportional to the well known Hermite ones¹⁴, and the explicit form of the normalization factor N_n is unnecessary for our aims.

The brief discussion given above has the sole purpose of calling the reader's attention on the close relationship between the correct asymptotic behaviour of the solution of the Schrödinger equation at $|x| \rightarrow \infty$ and the allowed values of the energy, as well as on the fact that $s/x - \psi'_n(x)/\psi_n(x)$ is a rational function, analytic at origin, and can be expanded in a Taylor series:

$$\frac{s}{x} - \frac{\psi'_n(x)}{\psi_n(x)} = \frac{xP_n(x) - P'_n(x)}{P_n(x)} = \sum_{j=0}^{\infty} f_j x^{2j+1} \quad (4)$$

III. THE RICCATI-PADÉ METHOD FOR THE HARMONIC OSCILLATOR

Suppose that we do not know the allowed values of the energy of the harmonic oscillator and consider the regularized logarithmic derivative of the eigenfunction

$$f(x) = \frac{s}{x} - \frac{\psi'(x)}{\psi(x)} \quad (5)$$

that satisfies the Riccati equation

$$f'(x) + \frac{2sf(x)}{x} - f(x)^2 + x^2 - E - \frac{s(s-1)}{x^2} = 0 \quad (6)$$

where the last term vanishes because $s = 0$ or $s = 1$ as discussed earlier. In order to derive this expression we simply differentiate $f(x)$ with respect to x and use equations (1) and (5) to get rid of $\psi''(x)/\psi(x)$ and $\psi'(x)/\psi(x)$. According to what was said above we know that we can expand $f(x)$ in a Taylor series about the origin

$$f(x) = x \sum_{j=0}^{\infty} f_j(E) z^j, \quad z = x^2 \quad (7)$$

Its substitution into the Riccati equation (6) leads to a recurrence relation for the coefficients f_j (see below) that enables us to obtain as many of them as necessary. The first few coefficients of this expansion when $s = 0$ are

$$\begin{aligned} f_0 &= E \\ f_1 &= \frac{E^2 - 1}{3} \\ f_2 &= \frac{2(E^2 - 1)E}{15} \\ f_3 &= \frac{(E^2 - 1)(17E^2 - 5)}{315} \end{aligned} \quad (8)$$

Their general form appears to be $f_j = (E^2 - 1)Q_j(E)$ for $j > 0$, where $Q_j(E)$ is a polynomial function of the energy.

Taking into account that the regularized logarithmic derivative of the eigenfunction is an exact rational function for the harmonic oscillator when $E = E_n$, as shown by equation (4), we look for a solution of the form $f(x) = x[M/N](x^2)$, where

$$[M/N](z) = \frac{\sum_{j=0}^M a_j z^j}{\sum_{j=0}^N b_j z^j} = \sum_{j=0}^{M+N+1} f_j(E) z^j + O(z^{M+N+2}) \quad (9)$$

Since we can arbitrarily choose $b_0 = 1$ we are left with $M + N + 1$ coefficients of the rational function and the unknown energy as independently adjustable parameters; therefore we can try to obtain $M + N + 2$ exact coefficients of the Taylor series for $f(x)$ as explicitly indicated in equation (9). When $M \geq N$ we easily derive the following equations:

$$\begin{aligned} \sum_{k=0}^{\min(j,N)} b_k f_{j-k} &= a_j, \quad j = 0, 1, \dots, M \\ \sum_{k=0}^N b_k f_{j-k} &= 0, \quad j = M + 1, M + 2, \dots, M + N + 1 \end{aligned} \quad (10)$$

We can view the second set as a system of $N+1$ homogeneous equations with $N+1$ unknowns $b_N, b_{N-1}, \dots, b_0$. Therefore, there will be a nontrivial solution if E is a root of

$$H_D^d(E) = \begin{vmatrix} f_{M-N+1} & f_{M-N+2} & \cdots & f_{M+1} \\ f_{M-N+2} & f_{M-N+3} & \cdots & f_{M+2} \\ \vdots & \vdots & \ddots & \vdots \\ f_{M+1} & f_{M+2} & \cdots & f_{M+N+1} \end{vmatrix} = 0 \quad (11)$$

where $d = M - N = 0, 1, \dots$ and $D = N + 1 = 2, 3, \dots$ is the dimension of the Hankel determinant $H_D^d(E)$. The first Hankel determinants for $s = 0$ are:

$$\begin{aligned} H_2^0(E) &= \frac{(E^2 - 1)^2(E^2 - 25)}{4725} \\ H_2^1(E) &= \frac{(E^2 - 1)^2(E^2 - 25)(E^2 + 3)}{297675} \\ H_3^0(E) &= \frac{(E^2 - 1)^3(E^2 - 25)^2(E^2 - 81)}{46414974375} \\ H_3^1(E) &= \frac{4(E^2 - 1)^3(E^2 - 25)^2(E^2 - 81)E}{896041080309375} \end{aligned} \quad (12)$$

The general form appears to be $H_D^d = (E^2 - 1)^D(E^2 - 25)^{D-1} \dots [E^2 - (4D - 3)^2]G_D^d(E)$ where $G_D^d(E)$ is a polynomial function of E . We appreciate that

- As D increases more exact eigenvalues appear as roots of $H_D^d(E) = 0$
- The multiplicity of each root increases with D
- In addition to the “physical” roots $E_n = 2n + 1$ there are spurious ones; for example: $-(2n + 1)$ (later on we will discuss the occurrence of such negative roots)
- We have obtained the allowed energies without taking into account the asymptotic behaviour of the eigenfunctions at large $|x|$ explicitly

IV. ANHARMONIC OSCILLATORS

In this section we generalize the main results derived above for the harmonic oscillator and develop the method for the Schrödinger equation

$$\psi''(x) + [E - V(x)]\psi(x) = 0 \quad (13)$$

where $V(x)$ is analytic at origin and symmetric about this point: $V(-x) = V(x)$. Without loss of generality we assume that $V(0) = 0$. Since we can expand $V(x)$ in a Taylor series

$$V(x) = \sum_{j=1}^{\infty} V_j x^{2j} \quad (14)$$

then we can apply the method exactly as indicated above for the harmonic oscillator. The regularized logarithmic derivative of the eigenfunction $f(x) = s/x - \psi'(x)/\psi(x)$ satisfies the Riccati equation

$$f'(x) + \frac{2sf(x)}{x} - f(x)^2 + V(x) - E = 0 \quad (15)$$

If we expand $f(x)$ in odd-power series as in equation (7) we easily calculate the coefficients f_j by means of the recurrence relation

$$\begin{aligned} f_n &= \frac{1}{2n + 2s + 1} \left(\sum_{j=0}^{n-1} f_j f_{n-j-1} + E\delta_{n0} - V_n \right), \quad n = 1, 2, \dots \\ f_0 &= \frac{E}{2s + 1} \end{aligned} \quad (16)$$

and then construct the rational approximation (9) that leads to the Hankel determinant (11). We do not expect to obtain exact eigenvalues for the general anharmonic oscillator as we have already done for the harmonic one, but at least we do expect that the roots of the Hankel determinants will enable us to estimate the eigenvalues of the Schrödinger equation (13). We call this approach Riccati–Padé method (RPM) because it is based on the Riccati equation for the modified logarithmic derivative of the eigenfunction, and a rational approximation or Padé approximant (9)¹⁵.

The simplest symmetric anharmonic potential is

$$V(x) = x^2 + \lambda x^4 \quad (17)$$

This model has been widely studied because the perturbation expansion

$$E(\lambda) = \sum_{j=0}^{\infty} E^{(j)} \lambda^j \quad (18)$$

is divergent^{15,16,17,18}. A straightforward argument based on scaling the coordinate of the Schrödinger equation shows that the energy can also be expanded as

$$E(\lambda) = \lambda^{1/3} \sum_{j=0}^{\infty} e^{(j)} \lambda^{-2j/3} \quad (19)$$

with a nonzero convergence radius^{15,18}.

From $H_2^0(E)$ we obtain (for concreteness we restrict to even states $s = 0$)

$$E^6 - 27E^4 + 162E^3\lambda + 51E^2 - 162E\lambda - 189\lambda^2 - 25 = 0 \quad (20)$$

Fig. 1 shows that this simple expression yields reasonable results for the ground state of the anharmonic oscillator (17) for all λ values. The roots $E(\lambda)$ of (20) can be expanded in λ -power series (18) and also in $\lambda^{-2/3}$ -power series (19). To prove the latter statement, simply substitute $\lambda^{1/3}W$ for E in equation (20) and notice that the roots of the resulting equation

$$W^6 - 27W^4\lambda^{-2/3} + 162W^3 + 51W^2\lambda^{-4/3} - 162W\lambda^{-2/3} - 25\lambda^{-2} - 189 = 0 \quad (21)$$

are functions of $\lambda^{-2/3}$. Besides, when $\lambda \rightarrow \infty$ we obtain

$$W^6 + 162W^3 - 189 = 0 \quad (22)$$

One of its roots $W \approx 1.05$ is quite close to the exact leading coefficient $e^{(0)}$ (calculated below) and explains why the simple expression (20) yields satisfactory results for all values of λ .

From $H_2^1(E)$ we obtain

$$E^8 - 24E^6 - 558E^5\lambda - 30E^4 + 1404E^3\lambda + (666\lambda^2 + 128)E^2 - 846E\lambda - 882\lambda^2 - 75 = 0 \quad (23)$$

It has been proved that roots of $H_D^0(E)$ and $H_D^1(E)$ are lower and upper bounds, respectively, to the eigenvalues of the Schrödinger equation with the potential (17)^{1,2}. Fig. 1 also shows the approximate ground-state eigenvalue given by Eq. (23) and we appreciate that the upper and lower bounds are quite close for all values of λ .

In order to test the rate of convergence of the RPM we consider the most difficult case $\lambda \rightarrow \infty$, sometimes called the strong-coupling limit. Since $\lim_{\lambda \rightarrow \infty} \lambda^{-1/3}E(\lambda) = e^{(0)}$ is an eigenvalue of $\hat{H} = \hat{p}^2 + \hat{x}^4$ we consider the potential

$$V(x) = x^4 \quad (24)$$

in what follows. Let $E_n^{[D,d]}$ be a sequence of roots of $H_D^d(E)$ that converges towards the energy eigenvalue E_n of the anharmonic oscillator with the potential (24). As said above, $E_n^{[D,0]}$ and $E_n^{[D,1]}$ converge towards E_n from below and above, respectively, as D increases, giving progressively tighter lower and upper bounds^{1,2}. Fig. 2 shows $\log |E_0^{[D,1]} - E_0^{[D,0]}|$ that is a measure of the rate of convergence of the bounds towards the ground-state eigenvalue as D increases. From straightforward linear regression we estimate that $|E_0^{[D,1]} - E_0^{[D,0]}| \approx 77.31e^{-4.43D}$, $D = 2, 3, \dots$. Not many approaches exhibit such remarkable exponential rate of convergence. We find that $E_0^{[11,0]} = 1.0603620904841828996$ is exact up to the last digit and that the accuracy of the RPM results increases with D according to the exponential rate of convergence just given.

The number of zeros of $\psi_n(x)$ increases with n and for that reason we need determinants of greater dimension to take into account the increasing oscillation of the excited states (think of the rational approximation to $f(x)$). For the first excited even state $n = 2$ we obtain $|E_2^{[D,1]} - E_2^{[D,0]}| \approx (8.02 \times 10^4) e^{-4.50D}$, $D = 3, 4, \dots$ and $E_2^{[12,0]} = 7.4556979379867383922$ is exact up to the last digit.

V. MULTIPLICITY OF ROOTS

In the case of the harmonic oscillator we saw that the multiplicity of each root increases with the determinant dimension. The counterpart of this unusual feature of the RPM in the case of problems that are not exactly solvable is the occurrence of many roots in the neighbourhood of the chosen eigenvalue. Fig. 3 shows $\log |E_0^{[D,0]} - E_0^{[\infty,0]}|$ for the anharmonic oscillator with the potential (24), where we have arbitrarily chosen $E_0^{[\infty,0]} = E_0^{[11,0]}$ for this numerical experiment. We appreciate that there are several parallel sequences of roots converging towards the ground-state eigenvalue. A straight line $\log |E_0^{[D,0]} - E_0^{[\infty,0]}| \approx 1.95(1 - D)$ marks the optimal sequence that was chosen above as a lower bound. The strategy for identifying the optimal sequence from the other ones consists simply in selecting the root of $H_D^d(E) = 0$ closest to the one chosen previously from $H_{D-1}^d(E) = 0$.

For the first even excited state we find $\log |E_2^{[D,0]} - E_2^{[\infty,0]}| \approx 4.85 - 1.95D$ which is parallel to the ground-state one.

VI. SPURIOUS ROOTS

The RPM may also yield roots that are not related to the eigenvalues of the chosen model. To understand this interesting feature of the approach consider the change of variables $x = \gamma q$ that transforms $\hat{H} = -d^2/dx^2 + V(x)$ into $\hat{H} = \gamma^{-2} [-d^2/dq^2 + \gamma^2 V(\gamma q)]$. Therefore, some roots of the Hankel determinant for $\hat{H}$ will also give us an approximation to γ^{-2} times the eigenvalues of $-d^2/dq^2 + \gamma^2 V(\gamma q)$ provided that $\gamma^2 V(\gamma q)$ is a “reasonable” potential–energy function¹⁰. For example, in the case of the harmonic oscillator $\gamma^2 V(\gamma q) = \gamma^4 q^2$ and the choice $\gamma^2 = -1$ explains the occurrence of the negative roots $-(2n + 1)$ discussed above.

It is interesting to consider the modified Posch–Teller potential¹⁹

$$V(x) = -\frac{\lambda(\lambda - 1)}{\cosh(x)^2} \quad (25)$$

with exact eigenvalues $E_n(MPT) = -(\lambda - 1 - n)^2$. The change of coordinates discussed above with $\gamma = i$ yields -1 times the Hamiltonian operator with the Posch–Teller potential¹⁹

$$V(q) = \frac{\lambda(\lambda - 1)}{\cos(q)^2} \quad (26)$$

and eigenvalues $E_n(PT) = (\lambda + 2n)^2$. We thus expect sequences of roots of the Hankel determinant converging towards $E_n(MPT)$ and $-E_n(PT)$ ¹⁰.

Table I shows them for $n = 0$ and $d = 0$. This example is greatly revealing because the asymptotic behaviour of the bound–state eigenfunctions of the first model (25) is $\psi(x \rightarrow \pm\infty) = 0$, whereas for the second one (26) the Dirichlet boundary conditions $\psi(\pm\pi/2) = 0$ are determined by the poles of the potential–energy function (26) at $\pm\pi/2$. We appreciate that the RPM yields solutions to two models with quite different boundary conditions simultaneously. This is partly a consequence of the fact that the RPM does not take the boundary conditions explicitly into account as discussed earlier in Sec. III.

VII. EIGENFUNCTIONS

Once we have a sufficiently accurate eigenvalue we obtain the coefficients f_j and the rational approximation (9) to $f(x)$. The approximate eigenfunction given by

$$\psi(x) = Nx^s e^{-\int^x f(y)dy} \quad (27)$$

will be accurate in a neighbourhood of the origin but in general will not satisfy the boundary conditions at infinity. In principle, one can use the accurate energy and coefficients to derive an improved expression for the eigenfunction that behaves satisfactorily at infinity. However, if one needs to calculate the expectation value of an operator $\hat{A}$ it is preferable to apply the RPM to $\hat{H} + \beta\hat{A}$ and calculate the slope $dE/d\beta$ at $\beta = 0$. According to the Hellmann–Feynman theorem we have²⁰

$$\frac{dE}{d\beta}(\beta) = \langle \hat{A} \rangle(\beta) \quad (28)$$

Straightforward differentiation of $H_D^d(E, \beta) = 0$ with respect of β leads to $dH_D^d/d\beta = (\partial H_D^d/\partial\beta)_E + (\partial H_D^d/\partial E)_\beta(dE/d\beta) = 0$ from which it follows that

$$\frac{dE}{d\beta} = -\frac{(\partial H_D^d/\partial\beta)_E}{(\partial H_D^d/\partial E)_\beta} \quad (29)$$

Fig. 4 shows the convergence of the RPM values for $\langle x^2 \rangle$ for the ground state of the anharmonic oscillator with potential (24) estimated by equations (28) and (29) at $\beta = 0$. In this case we simply apply the RPM to the anharmonic oscillator with potential–energy function $V(x) = x^4 + \beta x^2$ and obtain $\langle x^2 \rangle = 0.3620226487886768452$. It is worth noticing that $\langle x^2 \rangle = e^{(1)}$ is the second–leading coefficient of the series (19).

VIII. DOUBLE–WELL OSCILLATOR

The RPM developed above is also suitable for the calculation of the eigenvalues of the Schrödinger equation with symmetric double–well potentials. For concreteness and simplicity we consider the anharmonic oscillator with the potential–energy function

$$V(x) = x^4 + \beta x^2 \quad (30)$$

that exhibits two wells when $\beta < 0$. They are located at $x_w = \pm\sqrt{-\beta/2}$ and their depth is $V(x_w) = -\beta^2/4$.

As in the case of the anharmonic oscillator discussed above we find that the RPM provides lower and upper bounds: $E_n^{[D,0]} < E_n < E_n^{[D,1]}$. We first consider the implicit analytic expressions given by $H_2^0(E, \beta) = 0$, and $H_2^1(E, \beta) = 0$:

$$\begin{aligned} E^6 - 27E^4\beta + 162E^3 + 51E^2\beta^2 - 162E\beta - 25\beta^3 - 189 &= 0 \\ E^8 - 24E^6\beta - 558E^5 - 30E^4\beta^2 + 1404E^3\beta \\ + (666 + 128\beta^3)E^2 - 846E\beta^2 - 882\beta - 75\beta^4 &= 0 \end{aligned} \quad (31)$$

respectively. Fig. 5 and 6 shows the roots of these equations as functions of β . We appreciate that one branch of each equation agrees with the accurate results also plotted in those figures.

Fig. 7 shows $\log |E_0^{[D,1]} - E_0^{[D,0]}|$ for $D \leq 20$ and $\beta = -1, -5, -10, -15$, as well as straight lines provided by straightforward linear regression of the data for each value of β . We appreciate that the rate of convergence decreases slightly and the RPM sequences start at greater D as β becomes more negative. However, in all those cases the convergence of the RPM is remarkable. We obtain similar results for the first excited state. The rate of convergence of the RPM bounds is considerably greater to that of the moment method²². However, the latter method is more general and can be applied to a wider variety of problems.

Table II shows the first two eigenvalues obtained from Hankel determinants with $d = 0$, $d = 1$, and $D \leq 20$. The upper and lower bounds agree to 20 digits for all those values of β except for $\beta = -15$. In this case we estimate $-50.8413872843819547 < E_0 < -50.8413872843819543$ and $-50.8413872841870053 < E_1 < -50.8413872841870051$.

It is worth mentioning that present approach is based on a Taylor expansion of the solution about the top of the barrier, and it is well known that it is more convenient to expand about one of the minima. However, in the latter case we would have a nonsymmetric potential-energy function that we do not discuss here.

IX. CONCLUSIONS

In this paper we have presented an approach for the accurate calculation of eigenvalues and eigenfunctions of separable quantum-mechanical problems. In this introductory communication we have restricted to one-dimensional models with symmetric (even-parity) potential-energy functions. The generalization to other cases is straightforward and will be discussed in subsequent articles.

This presentation appears rather mathematical at first sight, but one must keep in mind that the Schrödinger equation for anharmonic oscillators have many applications in the study of, for example, oscillatory phenomena²¹. Therefore, the RPM may be of practical utility in such studies, particularly because its remarkable rate of convergence enables one to obtain accurate results easily. We would not say that the RPM is the best choice for all possible applications, but it is worth taking into consideration that it does not require the calculation of matrix elements which may be difficult for some potentials and only requires

their Taylor expansions. Besides, in some cases, like the anharmonic oscillator (17), the RPM yields simple implicit equations that are reasonably accurate for all values of the potential parameters.

But the main purpose of this paper is to discuss an approximate method that does not share many features with those presented in standard textbooks on quantum chemistry and quantum mechanics^{14,21}. It is those peculiar features of the RPM that in our opinion could make it most interesting for students with some knowledge in mathematics and physics. In particular, the RPM is suitable for training students in the use of CAS that facilitate most of the required algebra and analysis.

-
- ¹ F. M. Fernández, Q. Ma, and R. H. Tipping, “Tight upper and lower bounds for energy eigenvalues of the Schrödinger equation”, *Phys. Rev. A* **39**, 1605-1609 (1989).
 - ² F. M. Fernández, Q. Ma, and R. H. Tipping, “Eigenvalues of the Schrödinger equation via the Riccati-Padé method”, *Phys. Rev. A* **40**, 6149-6153 (1989).
 - ³ F. M. Fernández, “Strong Coupling Expansion for Anharmonic Oscillators and Perturbed Coulomb Potentials”, *Phys. Lett. A* **166**, 173-176 (1992).
 - ⁴ F. M. Fernández and R. Guardiola, “Accurate Eigenvalues and Eigenfunctions for Quantum-Mechanical Anharmonic Oscillators”, *J. Phys. A* **26**, 7169-7180 (1993).
 - ⁵ F. M. Fernández, R. Guardiola, and M. Znojil, “Riccati-Padé quantization and oscillators $V(r) = gr^a$ ”, *Phys. Rev. A* **48**, 4170-4174 (1993).
 - ⁶ F. M. Fernández, “Alternative Treatment of Separable Quantum-mechanical Models: the Hydrogen Molecular Ion”, *J. Chem. Phys.* **103**, 6581-6585 (1995).
 - ⁷ F. M. Fernández and R. H. Tipping, “The Riccati-Padé quantization method for one-dimensional quantum-mechanical models”, *Can. J. Phys.* **74**, 697-700 (1996).
 - ⁸ F. M. Fernández, “Direct Calculation of Accurate Siegert Eigenvalues”, *J. Phys. A* **28**, 4043-4051 (1995).
 - ⁹ F. M. Fernández, “Resonances for a Perturbed Coulomb Potential”, *Phys. Lett. A* **203**, 275-278 (1995).
 - ¹⁰ F. M. Fernández, “Quantization Condition for Bound and Quasibound States”, *J. Phys. A* **29**, 3167-3177 (1996).

- ¹¹ F. M. Fernández, “Direct Calculation of Stark Resonances in Hydrogen”, *Phys. Rev. A* **54**, 1206-1209 (1996).
- ¹² F. M. Fernández, “Calculation of bound states and resonances in perturbed Coulomb models”, *Phys. Lett. A* **372**, 2956-2958 (2008).
- ¹³ F. M. Fernández, ”The accurate calculation of resonances in multiple-well oscillators”, *J. Phys. A* **41**, 065202 (2008).
- ¹⁴ F. L. Pilar, *Elementary Quantum Chemistry*, (McGraw-Hill, New York, 1968).
- ¹⁵ C. M. Bender and S. A. Orszag, *Advanced mathematical methods for scientists and engineers*, (McGraw-Hill, New York, 1978).
- ¹⁶ C. M. Bender and T. T. Wu, “Anharmonic oscillator”, *Phys. Rev.* **185**, 1231-1260 (1969).
- ¹⁷ C. M. Bender and T. T. Wu, “Large-order behaviour of perturbation theory”, *Phys. Rev. Lett.* **27**, 461-465 (1971).
- ¹⁸ B. Simon, “Coupling constant analyticity for the anharmonic oscillator”, *Ann. Phys.* **58**, 76-136 (1970).
- ¹⁹ S. Flügge, *Practical Quantum Mechanics*, (Springer-Verlag, Berlin, 1999).
- ²⁰ F. M. Fernández, *Introduction to Perturbation Theory in Quantum Mechanics*, (CRC Press, Boca Raton, 2000).
- ²¹ C. Cohen–Tannoudji, B. Diu, and F. Laloë, *Quantum Mechanics*, (John Wiley & Sons, New York, 1977).
- ²² C. R. Handy, ”Application of the eigenvalue moment method to the quartic anharmonic double-well oscillator”, *Phys. Rev. A* **46**, 1663-1666 (1992)

TABLE I: Ground-state eigenvalues of the models in equations (25) and (26)

D	$E_0(25)$	$-E_0(26)$
2	-3.9988835968549022343	-8.9983715148790601222
3	-3.9999985313068943510	-8.9999994018534834235
4	-3.999999984549959290	-8.999999999381908008
5	-3.99999999984803299	-8.99999999999974948
6	-3.9999999999985472	-9.0000000000000000000
7	-3.9999999999999986	-9.0000000000000000000
8	-4.0000000000000000000	-9.0000000000000000000

TABLE II: Ground- and first-excited-state eigenvalues of the double-well oscillator (30)

β	E_0	E_1
-1	0.65765300518071512306	2.8345362021193042147
-5	-3.4101427612398294753	-3.2506753622892359802
-10	-20.633576702947799150	-20.633546884404911079
-15	-50.8413872843819543	-50.8413872841870051




FIG. 1: Ground-state energy of the anharmonic oscillator (17). The solid and dashed curves are the analytical lower (20) and upper (23) bounds, respectively, and the circles mark more accurate results




FIG. 2: Convergence of the upper and lower bounds to the ground-state energy of the anharmonic oscillator (24)




FIG. 3: Sequences of roots converging towards the ground-state energy of the anharmonic oscillator (24) as $\log|E_0^{[D,0]} - E_0^{[\infty,0]}|$




FIG. 4: Convergence of the upper and lower bounds to $\langle x^2 \rangle$ for the ground state of the anharmonic oscillator with potential (24)




FIG. 5: Roots $E(\beta)$ of $H_2^0(E, \beta) = 0$ (points) and accurate results (filled circles) for the ground state of the double-well oscillator (30)




FIG. 6: Roots $E(\beta)$ of $H_2^1(E, \beta) =$ (points) and accurate results (filled circles) for the ground state of the double-well oscillator (30)




FIG. 7: Logarithmic convergence of the lower and upper bounds $\log |E_0^{[D,1]} - E_0^{[D,0]}|$ for the ground state of the double-well oscillator (30) for $\beta = -1$ (squares), $\beta = -5$ (filled squares), $\beta = -10$ (circles), $\beta = -15$ (filled circles)